

GAME	NOTES	GAME SELECTION DIP SWITCH S5											CPU CLOCK JUMPERS		RAM WIDTH S6
		COMBO ROM 09-17-21											.5Mhz	.895Mhz	D0-D4
BALLY -17	REPLACING BALLY AS-2518-17	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4			
000	Black Jack	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	ON	ON	ON	ON	IN	OUT	OFF		
001	Eight Ball	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	ON	ON	ON	OFF	IN	OUT	OFF		
002	Evel Knivel	DIP 17, 18 & 19 ON for free play. Tilt exploit fixed. Drop target down logic.	ON	ON	ON	ON	ON	ON	OFF	ON	IN	OUT	OFF		
003	Freedom	DIP 17, 18 & 19 ON for free play. Tilt exploit fixed. Drop target down logic.	ON	ON	ON	ON	ON	ON	OFF	OFF	IN	OUT	OFF		
004	Mata Hari	DIP 17, 18 & 19 ON for free play. Drop target down logic.	ON	ON	ON	ON	ON	OFF	ON	ON	IN	OUT	OFF		
005	Night Rider	DIP 17, 18 & 19 ON for free play. Tilt exploit fixed. Drop target down logic.	ON	ON	ON	ON	ON	OFF	ON	OFF	IN	OUT	OFF		
006	Night Rider Custom	Home ROM by Seymour Shabow	ON	ON	ON	ON	ON	OFF	OFF	ON	IN	OUT	OFF		
007	Power Play	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	ON	OFF	OFF	OFF	IN	OUT	OFF		
008	Strikes and Spares	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	ON	OFF	ON	ON	IN	OUT	OFF		
BALLY -35	REPLACING BALLY AS-2518-35	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4			
009	Black Pyramid	DIP 25 & 26 ON for free play	ON	ON	ON	ON	OFF	ON	ON	OFF	IN	OUT	OFF		
010	BMX	DIP 25 & 26 ON for free play	ON	ON	ON	ON	OFF	ON	OFF	ON	IN	OUT	OFF		
011	Centaur	DIP 25 & 26 ON for free play	ON	ON	ON	ON	OFF	ON	OFF	OFF	IN	OUT	OFF		
012	Centaur Home V27	Home ROM by Oliver O.	ON	ON	ON	ON	OFF	OFF	ON	ON	IN	OUT	OFF		
013	Cybernaut	DIP 25 & 26 ON for free play	ON	ON	ON	ON	OFF	OFF	ON	OFF	IN	OUT	OFF		
014	Dolly	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	ON	ON	OFF	OFF	OFF	ON	IN	OUT	OFF		
015	Eight Ball Deluxe	DIP 25 & 26 ON for free play. Multiplayer bonus bug fixed.	ON	ON	ON	ON	OFF	OFF	OFF	OFF	IN	OUT	OFF		
016	Eight Ball Deluxe Home V32	Home ROM by Oliver O.	ON	ON	ON	OFF	ON	ON	ON	ON	IN	OUT	OFF		
017	Elektra	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	ON	ON	OFF	IN	OUT	OFF		
018	Embryon	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	ON	OFF	ON	IN	OUT	OFF		
019	Embryon Home R9	Home ROM by Oliver O. DIP 32=OFF for 7 digit displays	ON	ON	ON	OFF	ON	ON	OFF	OFF	IN	OUT	OFF		
020	Fathom	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	OFF	ON	ON	IN	OUT	OFF		
021	Fathom Home V5	Home ROM by Oliver O.	ON	ON	ON	OFF	ON	OFF	ON	OFF	IN	OUT	OFF		
022	Fireball Classic	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	OFF	OFF	ON	IN	OUT	OFF		
023	Fireball II	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	OFF	OFF	OFF	IN	OUT	OFF		
024	Flash Gordon	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	OFF	ON	ON	ON	IN	OUT	OFF		
025	Flash Gordon French	DIP 25 & 26 ON for free play. French Language	ON	ON	ON	OFF	OFF	ON	ON	OFF	IN	OUT	OFF		
026	Frontier	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	OFF	ON	OFF	ON	IN	OUT	OFF		
027	Future Spa	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	ON	OFF	OFF	ON	OFF	OFF	IN	OUT	OFF		
028	Harlem Globetrotters	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	ON	OFF	OFF	OFF	ON	ON	IN	OUT	OFF		
029	Holdoggin'	DIP 25 & 26 ON for free play. DIP27 OFF for reset letters at EOB	ON	ON	ON	OFF	OFF	OFF	ON	OFF	IN	OUT	OFF		
030	Kings of Steel	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	OFF	OFF	OFF	ON	IN	OUT	OFF		
031	Kiss	DIP 17, 18 & 19 ON for free play	ON	ON	ON	OFF	OFF	OFF	OFF	OFF	IN	OUT	OFF		
032	Kiss 7-Digit	7 Digit Displays. No free play.	ON	ON	OFF	ON	ON	ON	ON	ON	IN	OUT	OFF		
033	Lost World	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	ON	ON	ON	ON	OFF	IN	OUT	OFF		
034	Medusa	DIP 25 & 26 ON for free play	ON	ON	OFF	ON	ON	ON	OFF	ON	IN	OUT	OFF		
035	Mr and Mrs Pacman	DIP 25 & 26 ON for free play	ON	ON	OFF	ON	ON	ON	OFF	OFF	IN	OUT	OFF		
036	Mystic	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	ON	ON	OFF	ON	ON	IN	OUT	OFF		
037	Nitro Ground Shaker	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	ON	ON	OFF	ON	OFF	IN	OUT	OFF		
038	Paragon	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	ON	ON	OFF	OFF	ON	IN	OUT	OFF		
039	Paragon 7-Digit	7 Digit Displays. No free play	ON	ON	OFF	ON	ON	OFF	OFF	OFF	IN	OUT	OFF		
040	Playboy	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	ON	OFF	ON	ON	ON	IN	OUT	OFF		
041	Playboy 7-Digit	7 Digit Displays. No free play	ON	ON	OFF	ON	OFF	ON	ON	OFF	IN	OUT	OFF		
042	Rolling Stones	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	ON	OFF	ON	OFF	ON	IN	OUT	OFF		
043	Silverball Mania	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	ON	OFF	ON	OFF	OFF	IN	OUT	OFF		
044	Skateball	DIP 25 & 26 ON for free play	ON	ON	OFF	ON	OFF	OFF	ON	ON	IN	OUT	OFF		
045	Skateball Home	DIP 25 & 26 ON for free play. Improved attract mode lighting.	ON	ON	OFF	ON	OFF	OFF	ON	OFF	IN	OUT	OFF		
046	Space Invaders	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	ON	OFF	OFF	OFF	ON	IN	OUT	OFF		
047	Speakeasy 4 Player	DIP 25 & 26 ON for free play	ON	ON	OFF	ON	OFF	OFF	OFF	OFF	IN	OUT	OFF		
048	Speakeasy 2 Player	DIP 25 & 26 ON for free play	ON	ON	OFF	OFF	ON	ON	ON	ON	IN	OUT	OFF		
049	Spectrum	DIP 25 & 26 ON for free play	ON	ON	OFF	OFF	ON	ON	ON	OFF	IN	OUT	OFF		
050	Not Used	Not used	ON	ON	OFF	OFF	ON	ON	OFF	ON	IN	OUT	OFF		
051	Spy Hunter	DIP 25 & 26 ON for free play.	ON	ON	OFF	OFF	ON	ON	OFF	OFF	IN	OUT	OFF		
052	Star Trek	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	OFF	ON	OFF	ON	ON	IN	OUT	OFF		
053	Star Trek	7 Digit Displays. No free play	ON	ON	OFF	OFF	ON	OFF	ON	OFF	IN	OUT	OFF		
054	Supersonic	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	OFF	ON	OFF	OFF	ON	IN	OUT	OFF		
055	Supersonic	7 Digit Displays. No free play	ON	ON	OFF	OFF	ON	OFF	OFF	OFF	IN	OUT	OFF		
056	The Six Million Dollar Man	DIP 17, 18 & 19 ON for free play. DIP31 must be OFF.	ON	ON	OFF	OFF	OFF	ON	ON	ON	IN	OUT	OFF		
057	The Six Million Dollar Man	7 Digit Displays. No free play	ON	ON	OFF	OFF	OFF	ON	ON	OFF	IN	OUT	OFF		
058	Vector	DIP 25 & 26 ON for free play	ON	ON	OFF	OFF	OFF	ON	OFF	ON	IN	OUT	OFF		
059	Vector Home V5	Home ROM by Oliver O.	ON	ON	OFF	OFF	OFF	ON	OFF	OFF	IN	OUT	OFF		
060	Viking	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	OFF	OFF	OFF	ON	ON	IN	OUT	OFF		
061	Voltan Escapes Cosmic Doom	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	OFF	OFF	OFF	ON	OFF	IN	OUT	OFF		
062	Voltan Escapes Cosmic Doom	7 Digit Displays. No free play	ON	ON	OFF	OFF	OFF	OFF	OFF	ON	IN	OUT	OFF		
063	X's and O's	DIP 25 & 26 ON for free play	ON	ON	OFF	OFF	OFF	OFF	OFF	OFF	IN	OUT	OFF		
064	Xenon	DIP 25 & 26 ON for free play	ON	OFF	ON	ON	ON	ON	ON	ON	IN	OUT	OFF		
STERN MPU-100	REPLACING STERN MPU-100	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4			
065	Cosmic Princess	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	ON	ON	OFF	IN	OUT	OFF		
066	Dracula	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	ON	OFF	ON	IN	OUT	OFF		
067	Hot Hand	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	ON	OFF	OFF	IN	OUT	OFF		
068	Lectronamo	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	OFF	ON	ON	IN	OUT	OFF		
065	Magic	Same ROM as Cosmic Princess	ON	OFF	ON	ON	ON	ON	ON	OFF	IN	OUT	OFF		
069	Memory Lane	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	OFF	ON	OFF	IN	OUT	OFF		
068	Nugent	Same ROM as Lectronamo	ON	OFF	ON	ON	ON	OFF	ON	ON	IN	OUT	OFF		
070	Pinball	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	OFF	OFF	ON	IN	OUT	OFF		
071	Stars	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	OFF	OFF	OFF	IN	OUT	OFF		
070	Stingray	Same ROM as Pinball	ON	OFF	ON	ON	ON	OFF	OFF	ON	IN	OUT	OFF		
072	Trident	Factory Modified ROM P11A. Unknown changes. No free play.	ON	OFF	ON	ON	OFF	ON	ON	ON	IN	OUT	OFF		
073	Trident	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	OFF	ON	ON	OFF	IN	OUT	OFF		
066	Wild Fyre	Same ROM as Dracula	ON	OFF	ON	ON	ON	ON	OFF	ON	IN	OUT	OFF		
STERN MPU-200 **	REPLACING STERN MPU-200	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4			
074	Ali	Stock ROM. No free play	ON	OFF	ON	ON	ON	ON	ON	ON	OUT	IN	ON		
075	Ali	Always free play	ON	OFF	ON	ON	OFF	ON	OFF	OFF	OUT	IN	ON		
076	Big Game	Stock ROM. No free play	ON	OFF	ON	ON	OFF	ON	ON	ON	OUT	IN	ON		
077	Big Game	Always free play	ON	OFF	ON	ON	OFF	OFF	ON	OFF	OUT	IN	ON		
134	Big Game V9	Custom ROM. See website for info txt	OFF	ON	ON	ON	ON	OFF	OFF	ON	OUT	IN	ON		

GAME	NOTES	GAME SELECTION DIP SWITCH S5										CPU CLOCK JUMPERS		RAM WIDTH S6
		COMBO ROM 09-17-21										.5Mhz	.895Mhz	D0-D4
STERN MPU-200 **	REPLACING STERN MPU-200	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	DIP-9	DIP-10	B1	S1	DIP-1 TO DIP-4
078	Catacomb	Stock ROM. No free play	ON	OFF	ON	ON	OFF	OFF	OFF	ON	OUT	IN	ON	
079	Catacomb	Always free play	ON	OFF	ON	ON	OFF	OFF	OFF	ON	OUT	IN	ON	
080	Cheetah	Stock ROM. No free play	ON	OFF	ON	OFF	ON	ON	ON	ON	OUT	IN	ON	
081	Cheetah	Stock ROM. B16 version. No free play	ON	OFF	ON	OFF	ON	ON	ON	OFF	OUT	IN	ON	
082	Cheetah	Always free play	ON	OFF	ON	OFF	ON	ON	OFF	ON	OUT	IN	ON	
083	Cheetah Home	Only one collect bonus per ball.	ON	OFF	ON	OFF	ON	ON	OFF	OFF	OUT	IN	ON	
084	Dragonfist	Stock ROM. No free play	ON	OFF	ON	OFF	ON	OFF	ON	ON	OUT	IN	ON	
085	Dragonfist	Always free play	ON	OFF	ON	OFF	ON	OFF	ON	OFF	OUT	IN	ON	
086	Dragonfist Home v1106	Bonus X bug fix. DIP 19 ON = Free play	ON	OFF	ON	OFF	ON	OFF	OFF	ON	OUT	IN	ON	
087	Flight 2000	Stock ROM. No free play	ON	OFF	ON	OFF	ON	OFF	OFF	OFF	OUT	IN	ON	
088	Flight 2000	Always free play	ON	OFF	ON	OFF	OFF	ON	ON	ON	OUT	IN	ON	
132	Flight 2000 V3347	Custom ROM *** WARNING *** READ INFO FIRST. See website for info txt	OFF	ON	ON	ON	ON	ON	ON	ON	OUT	IN	ON	
089	Freefall	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	ON	ON	OFF	OUT	IN	ON	
090	Freefall	Always free play	ON	OFF	ON	OFF	OFF	ON	OFF	ON	OUT	IN	ON	
091	Galaxy	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	ON	OFF	OFF	OUT	IN	ON	
092	Galaxy	Always free play	ON	OFF	ON	OFF	OFF	OFF	ON	ON	OUT	IN	ON	
093	Iron Maiden	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	OFF	ON	OFF	OUT	IN	ON	
094	Iron Maiden	Always free play	ON	OFF	ON	OFF	OFF	OFF	OFF	ON	OUT	IN	ON	
095	Lightning	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	OFF	OFF	OFF	OUT	IN	ON	
096	Lightning	Always free play	ON	OFF	OFF	ON	ON	ON	ON	ON	OUT	IN	ON	
097	Meteor	Stock ROM. No free play. Factory Bonus X underflow to 256X bug fix	ON	OFF	OFF	ON	ON	ON	ON	OFF	OUT	IN	ON	
098	Meteor 7 Digit	V24 7 Digit Displays	ON	OFF	OFF	ON	ON	ON	OFF	ON	OUT	IN	ON	
099	Meteor Divide by 10	Scoring divided by ten. No free play	ON	OFF	OFF	ON	ON	ON	OFF	OFF	OUT	IN	ON	
100	Meteor Free	Always free play	ON	OFF	OFF	ON	ON	OFF	ON	ON	OUT	IN	ON	
135	Meteor V66	Custom ROM. See website for info txt	OFF	ON	ON	ON	ON	OFF	OFF	OFF	OUT	IN	ON	
137	Meteor V77	Custom ROM. See website for info txt	OFF	ON	ON	ON	OFF	ON	ON	OFF	OUT	IN	ON	
101	Nine Ball	Stock Rom. No free play	ON	OFF	OFF	ON	ON	OFF	ON	OFF	OUT	IN	ON	
102	Nine Ball	Always free play	ON	OFF	OFF	ON	ON	OFF	OFF	ON	OUT	IN	ON	
138	Nine Ball V14	*** BETA *** Custom Rom. Spinner Flips counted	OFF	ON	ON	ON	OFF	ON	OFF	ON	OUT	IN	ON	
103	Orbitor One	Stock Rom. No free play	ON	OFF	OFF	ON	ON	OFF	OFF	OFF	OUT	IN	ON	
104	Orbitor One	Always free play	ON	OFF	OFF	ON	OFF	ON	ON	ON	OUT	IN	ON	
105	Orbitor One	No minimum game time. Always free play	ON	OFF	OFF	ON	OFF	ON	ON	OFF	OUT	IN	ON	
106	Quicksilver	Stock Rom. No free play	ON	OFF	OFF	ON	OFF	ON	OFF	ON	OUT	IN	ON	
107	Quicksilver	Always free play	ON	OFF	OFF	ON	OFF	ON	OFF	OFF	OUT	IN	ON	
136	Quicksilver V7	Custom ROM. See website for info txt	OFF	ON	ON	ON	OFF	ON	ON	ON	OUT	IN	ON	
108	Seawitch	Stock Rom. No free play	ON	OFF	OFF	ON	OFF	OFF	ON	ON	OUT	IN	ON	
109	Seawitch	Always free play	ON	OFF	OFF	ON	OFF	OFF	ON	OFF	OUT	IN	ON	
110	Split Second	Stock Rom. No free play	ON	OFF	OFF	ON	OFF	OFF	OFF	ON	OUT	IN	ON	
111	Split Second	Always free play	ON	OFF	OFF	ON	OFF	OFF	OFF	OFF	OUT	IN	ON	
112	Star Gazer	Stock Rom. No free play	ON	OFF	OFF	OFF	ON	ON	ON	ON	OUT	IN	ON	
113	Star Gazer	Always free play	ON	OFF	OFF	OFF	ON	ON	ON	OFF	OUT	IN	ON	
114	Star Gazer Home R9	Home ROM by Oliver O.	ON	OFF	OFF	OFF	ON	ON	OFF	ON	OUT	IN	ON	
129	Star Gazer Seymour Home V6	Cntr drops for bot roll overs. L/R banks for spinner 10x. Bonus X halved	OFF	ON	ON	ON	ON	ON	ON	OFF	OUT	IN	ON	
115	Viper	Stock Rom. No free play	ON	OFF	OFF	OFF	ON	ON	OFF	OFF	OUT	IN	ON	
116	Viper	Always free play	ON	OFF	OFF	OFF	ON	OFF	ON	ON	OUT	IN	ON	
Bally Video and Special	REPLACING AS-2518-133 and Conversion Kits	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	DIP-9	DIP-10	B1	S1	DIP-1 TO DIP-4
117	Baby Pacman	No free play.	ON	OFF	OFF	OFF	ON	OFF	ON	OFF	IN	OUT	OFF	
118	Granny and the Gators	No free play.	ON	OFF	OFF	OFF	ON	OFF	OFF	ON	IN	OUT	OFF	
119	Grand Slam 2 Player	DIP 25 & 26 ON for free play	ON	OFF	OFF	OFF	ON	OFF	OFF	OFF	IN	OUT	OFF	
120	Grand Slam 4 Player	DIP 25 & 26 ON for free play	ON	OFF	OFF	OFF	OFF	ON	ON	ON	IN	OUT	OFF	
121	Goldball	No free play.	ON	OFF	OFF	OFF	OFF	ON	ON	OFF	IN	OUT	OFF	
122	Goldball Home	Home ROM by Oliver O.	ON	OFF	OFF	OFF	OFF	ON	OFF	ON	IN	OUT	OFF	
123	Mystic Star	No free play	ON	OFF	OFF	OFF	OFF	ON	OFF	OFF	IN	OUT	OFF	
124	World Defender	No free play	ON	OFF	OFF	OFF	OFF	OFF	ON	ON	IN	OUT	OFF	
125	Super Bowl	No free play	ON	OFF	OFF	OFF	OFF	OFF	ON	OFF	IN	OUT	OFF	
126	Super Bowl	Custom Free play ROM by Quench	ON	OFF	OFF	OFF	OFF	OFF	OFF	ON	IN	OUT	OFF	
127	Saturn 2	No free play	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF	IN	OUT	OFF	
128	Midnight Mauraders		OFF	ON	ON	ON	ON	ON	ON	ON	IN	OUT	OFF	
130	Rapid Fire		OFF	ON	ON	ON	ON	ON	OFF	ON	IN	OUT	OFF	
131	Black Beauty	Stern Shuffle Board	OFF	ON	ON	ON	ON	ON	OFF	OFF	IN	OUT	OFF	
133	Monroe Bowl	Monroe Bowl Bowler	OFF	ON	ON	ON	ON	OFF	ON	OFF	IN	OUT	OFF	
254	MEMORY CLEAR **	When the LED begins to blink the memory will be cleared.	OFF	OFF	OFF	OFF	OFF	OFF	OFF	ON	EITHER B1 OR S1 IN		ON	

**NOTES:**

RAM width is a four position DIP switch. All switches down for Bally and Stern MPU-100 games. All switches up for MPU-200 games.

B1 and S1 jumpers set the CPU clock speed. B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). S IN for 0.895MHz (Stern MPU-200)

Jumper shunt U2 Enable is removed when the U1 expanded ROM socket is used.

Clear audits to 00 with the Test and NMI Audit Clear buttons on the MPU after switching games. Push the test button until 01 appears on the credit/match display, then use NMI to clear.

Starting in Revision 14 the game select dip switch is orientated so UP is on and DOWN is off.

The blue adjustment pot labeled dispaly interrupt sets how often the displays are updated. This is mostly used for seven digit games, adjust until the displays look the best.

**\*\* If you experience wrong sounds in a Stern Meteor use the MEMORY CLEAR software (DEC # 254). Power up and when the LED begins to blink the memory has been cleared.**

**\*\*\* DIP 21 Must be off when using original six digit displays in a game that supports seven digit displays.**

**MPU Setup pictures at <http://nvr.am.weebly.com/mpu.html>**