	CAME	NOTES			CAME	SELCTIO	N DID CW	ITCU CE			CBU CLOC	V IIIMDEDĖ	RAM WIDTH S6
	GAME	NOTES COMBO ROM 06-12-21	A20	A19	A18	A17	A16	A15	A14	A13	.5Mhz	.895Mhz	D0-D4
	BALLY -17	REPLACING BALLY AS-2518-17	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4
000	Black Jack	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	ON	ON	ON	ON	IN	OUT	OFF
001	Eight Ball	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	ON	ON	ON	OFF	IN	OUT	OFF
002 003	Evel Knievel	DIP 17, 18 & 19 ON for free play. Tilt exploit fixed. Drop target down logic.	ON ON	ON	ON	ON	ON	ON	OFF OFF	ON OFF	IN IN	OUT	OFF OFF
003	Freedom Mata Hari	DIP 17, 18 & 19 ON for free play. Tilt exploit fixed. Drop target down logic. DIP 17, 18 & 19 ON for free play. Drop target down logic.	ON	ON	ON	ON	ON	OFF	OFF	OFF	IN	OUT	OFF
005	Night Rider	DIP 17, 18 & 19 ON for free play. Tilt exploit fixed. Drop target down logic.	ON	ON	ON	ON	ON	OFF	ON	OFF	IN	OUT	OFF
006	Night Rider Custom	Home ROM by Seymour Shabow	ON	ON	ON	ON	ON	OFF	OFF	ON	IN	OUT	OFF
007	Power Play	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	ON	OFF	OFF	OFF	IN	OUT	OFF
800	Strikes and Spares	DIP 17, 18 & 19 ON for free play. Enhanced Switch Test	ON	ON	ON	ON	OFF	ON	ON	ON	IN	OUT	OFF
000	BALLY -35	REPLACING BALLY AS-2518-35	DIP-1 ON	DIP-2 ON	DIP-3	DIP-4 ON	OFF	DIP-6	DIP-7	DIP-8 OFF	B1 IN	S1 OUT	OFF
009	Black Pyramid BMX	DIP 25 & 26 ON for free play DIP 25 & 26 ON for free play	ON	ON	ON	ON	OFF	ON	ON OFF	OFF	IN	OUT	OFF
011	Centaur	DIP 25 & 26 ON for free play	ON	ON	ON	ON	OFF	ON	OFF	OFF	IN	OUT	OFF
012	Centaur Home V27	Home ROM by Oliver O.	ON	ON	ON	ON	OFF	OFF	ON	ON	IN	OUT	OFF
013	Cybernaut	DIP 25 & 26 ON for free play	ON	ON	ON	ON	OFF	OFF	ON	OFF	IN	OUT	OFF
014	Dolly	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	ON	ON	OFF	OFF	OFF	ON	IN	OUT	OFF
015 016	Eight Ball Deluxe	DIP 25 & 26 ON for free play. Multiplayer bonus bug fixed.	ON ON	ON	ON	ON OFF	OFF	OFF	OFF	OFF	IN IN	OUT	OFF OFF
017	Eight Ball Deluxe Home V32 Elektra	Home ROM by Oliver O. DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	ON	ON	OFF	IN	OUT	OFF
018	Embryon	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	ON	OFF	ON	IN	OUT	OFF
019	Embryon Home R9	Home ROM by Oliver O. DIP 32=OFF for 7 digit displays	ON	ON	ON	OFF	ON	ON	OFF	OFF	IN	OUT	OFF
020	Fathom	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	ON	OFF	ON	ON	IN	OUT	OFF
021	Fathom Home V5	Home ROM by Oliver O.	ON	ON	ON	OFF	ON	OFF	ON	OFF	IN	OUT	OFF
022 023	Fireball II	DIP 25 & 26 ON for free play	ON ON	ON	ON	OFF	ON	OFF	OFF OFF	ON	IN IN	OUT	OFF OFF
023	Fireball II Flash Gordon	DIP 25 & 26 ON for free play DIP 25 & 26 ON for free play	ON	ON	ON	OFF	OFF	OFF	OFF	OFF	IN IN	OUT	OFF OFF
025	Flash Grodon French	DIP 25 & 26 ON for free play DIP 25 & 26 ON for free play. French Language	ON	ON	ON	OFF	OFF	ON	ON	OFF	IN	OUT	OFF
026	Frontier	DIP 25 & 26 ON for free play	ON	ON	ON	OFF	OFF	ON	OFF	ON	IN	OUT	OFF
027	Future Spa	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	ON	OFF	OFF	ON	OFF	OFF	IN	OUT	OFF
028	Harlem Globetrotters	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	ON	OFF	OFF	OFF	ON	ON	IN	OUT	OFF
029 030	Hotdoggin'	DIP 25 & 26 ON for free play. DIP27 OFF for reset letters at EOB DIP 25 & 26 ON for free play	ON ON	ON	ON ON	OFF OFF	OFF OFF	OFF OFF	ON OFF	OFF	IN IN	OUT	OFF OFF
030	Kings of Steel Kiss	DIP 17, 18 & 19 ON for free play	ON	ON	ON	OFF	OFF	OFF	OFF	OFF	IN	OUT	OFF
032	Kiss 7-Digit	7 Digit displays. No free play.	ON	ON	OFF	ON	ON	ON	ON	ON	IN	OUT	OFF
033	Lost World	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	ON	ON	ON	ON	OFF	IN	OUT	OFF
034	Medusa	DIP 25 & 26 ON for free play	ON	ON	OFF	ON	ON	ON	OFF	ON	IN	OUT	OFF
035	Mr and Mrs Pacman	DIP 25 & 26 ON for free play	ON	ON	OFF	ON	ON	ON	OFF	OFF	IN	OUT	OFF
036 037	Mystic	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON ON	ON	OFF OFF	ON	ON	OFF OFF	ON	ON OFF	IN IN	OUT	OFF OFF
037	Nitro Ground Shaker Paragon	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. *** DIP 17, 18 & 19 ON for free play	ON	ON	OFF	ON	ON	OFF	OFF	OFF	IN	OUT	OFF
039	Paragon 7-Digit	7 Digit Displays. No free play	ON	ON	OFF	ON	ON	OFF	OFF	OFF	IN	OUT	OFF
040	Playboy	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	ON	OFF	ON	ON	ON	IN	OUT	OFF
041	Playboy 7-Digit	7 Digit Displays. No free play	ON	ON	OFF	ON	OFF	ON	ON	OFF	IN	OUT	OFF
042	Rolling Stones	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	ON	OFF	ON	OFF	ON	IN	OUT	OFF
043 044	Silverball Mania Skateball	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. *** DIP 25 & 26 ON for free play	ON ON	ON	OFF OFF	ON	OFF OFF	ON OFF	OFF ON	OFF	IN IN	OUT	OFF OFF
045	Skateball Home	DIP 25 & 26 ON for free play. Improved attract mode lighting.	ON	ON	OFF	ON	OFF	OFF	ON	OFF	IN	OUT	OFF
046	Space Invaders	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	ON	OFF	OFF	OFF	ON	IN	OUT	OFF
047	Speakeasy 4 Player	DIP 25 & 26 ON for free play	ON	ON	OFF	ON	OFF	OFF	OFF	OFF	IN	OUT	OFF
048	Speakeasy 2 Player	DIP 25 & 26 ON for free play	ON	ON	OFF	OFF	ON	ON	ON	ON	IN	OUT	OFF
049 050	Spectrum	DIP 25 & 26 ON for free play	ON ON	ON	OFF	OFF OFF	ON	ON	ON OFF	OFF	IN IN	OUT	OFF OFF
050	Not Used Spy Hunter	DIP 25 & 26 ON for free play.	ON	ON	OFF	OFF	ON	ON	OFF	OFF	IN IN	OUT	OFF
052	Star Trek	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	OFF	ON	OFF	ON	ON	IN	OUT	OFF
053	Star Trek	7 Digit Displays. No free play	ON	ON	OFF	OFF	ON	OFF	ON	OFF	IN	OUT	OFF
054	Supersonic	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	OFF	ON	OFF	OFF	ON	IN	OUT	OFF
055	Supersonic	7 Digit Displays. No free play	ON	ON	OFF	OFF	ON	OFF	OFF	OFF	IN	OUT	OFF
056	The Six Million Dollar Man	DIP 17, 18 & 19 ON for free play. DIP31 must be OFF.	ON	ON	OFF	OFF	OFF	ON	ON	ON	IN	OUT	OFF
057 058	The Six Million Dollar Man Vector	7 Digit Displays, No free play DIP 25 & 26 ON for free play	ON ON	ON	OFF OFF	OFF OFF	OFF OFF	ON	ON OFF	OFF ON	IN IN	OUT	OFF OFF
059	Vector Home V5	Home ROM by Oliver O.	ON	ON	OFF	OFF	OFF	ON	OFF	OFF	IN	OUT	OFF
060	Viking	DIP 25 & 26 ON for free play. DIP21 ON for 7 digit display. ***	ON	ON	OFF	OFF	OFF	OFF	ON	ON	IN	OUT	OFF
061	-	DIP 17, 18 & 19 ON for free play	ON	ON	OFF	OFF	OFF	OFF	ON	OFF	IN	OUT	OFF
062	Voltan Escapes Cosmic Doom	7 Digit Displays, No free play	ON	ON	OFF	OFF	OFF	OFF	OFF	ON	IN	OUT	OFF
063 064	X's and O's	DIP 25 & 26 ON for free play	ON ON	ON OFF	OFF	OFF ON	OFF	OFF	OFF ON	OFF ON	IN IN	OUT	OFF OFF
004	Xenon STERN MPU-100	DIP 25 & 26 ON for free play REPLACING STERN MPU-100	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4
065	Cosmic Princess	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	ON	ON	OFF	IN	OUT	OFF
066	Dracula	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	ON	OFF	ON	IN	OUT	OFF
067	Hot Hand	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	ON	OFF	OFF	IN	OUT	OFF
068	Lectronamo	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	OFF	ON	ON	IN	OUT	OFF
065	Magic Memory Lane	Same ROM as Cosmic Princess DIR 20 ON for free play Credit Display Always On	ON	OFF	ON	ON	ON	ON	ON	OFF	IN IN	OUT	OFF OFF
069 068	Memory Lane Nugent	DIP 20 ON for free play. Credit Display Always On. Same ROM as Lectronamo	ON ON	OFF	ON	ON	ON	OFF	ON	OFF	IN IN	OUT	OFF
070	Pinball	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	OFF	OFF	ON	IN	OUT	OFF
071	Stars	DIP 20 ON for free play. Credit Display Always On.	ON	OFF	ON	ON	ON	OFF	OFF	OFF	IN	OUT	OFF
070	Stingray	Same ROM as Pinball	ON	OFF	ON	ON	ON	OFF	OFF	ON	IN	OUT	OFF
072	Trident	Factory Modified ROM P11A. Unknown changes. No free play.	ON	OFF	ON	ON	OFF	ON	ON	ON	IN	OUT	OFF
073 066	Trident Wild Fyre	DIP 20 ON for free play. Credit Display Always On. Same ROM as Dracula	ON ON	OFF OFF	ON	ON	OFF	ON	ON OFF	OFF	IN IN	OUT	OFF OFF
000	STERN MPU-200 **	REPLACING STERN MPU-200	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4
074	Ali	Stock ROM. No free play	ON	OFF	ON	ON	OFF	ON	OFF	ON	OUT	IN	ON
075	Ali	Always free play	ON	OFF	ON	ON	OFF	ON	OFF	OFF	OUT	IN	ON
076	Big Game	Stock ROM. No free play	ON	OFF	ON	ON	OFF	OFF	ON	ON	OUT	IN	ON
077	Big Game	Always free play	ON	OFF	ON	ON	OFF	OFF	ON	OFF	OUT	IN	ON
134	Big Game V8	Custom ROM. See website for info txt	OFF	ON	ON	ON	ON	OFF	OFF	ON	OUT	IN	ON
L													

	GAME	NOTES	GAME SELCTION DIP SWITCH S5 CPU CLOCK JUMPERS									RAM WIDTH S6	
		COMBO ROM 06-12-21	A20	A19	A18	A17	A16	A15	A14	A13	.5Mhz	.895Mhz	D0-D4
	STERN MPU-200 **	REPLACING STERN MPU-200	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4
078	Catacomb	Stock ROM. No free play	ON	OFF	ON	ON	OFF	OFF	OFF	ON	OUT	IN	ON
079	Catacomb	Always free play	ON	OFF	ON	ON	OFF	OFF	OFF	OFF	OUT	IN	ON
080	Cheetah	Stock ROM. No free play	ON	OFF	ON	OFF	ON	ON	ON	ON	OUT	IN	ON
081	Cheetah	Stock ROM. B16 version. No free play	ON	OFF	ON	OFF	ON	ON	ON	OFF	OUT	IN	ON
082	Cheetah	Always free play	ON	OFF	ON	OFF	ON	ON	OFF	ON	OUT	IN	ON
083	Cheetah Home	Only one collect bonus per ball.	ON	OFF	ON	OFF	ON	ON	OFF	OFF	OUT	IN	ON
084	Dragonfist	Stock ROM. No free play	ON	OFF	ON	OFF	ON	OFF	ON	ON	OUT	IN	ON
085	Dragonfist	Always free play	ON	OFF	ON	OFF	ON	OFF	ON	OFF	OUT	IN	ON
086	Dragonfist Home v1106	Bonus X bug fix. DIP 19 ON = Free play	ON	OFF	ON	OFF	ON	OFF	OFF	ON	OUT	IN	ON
087	Flight 2000	Stock ROM. No free play	ON	OFF	ON	OFF	ON	OFF	OFF	OFF	OUT	IN	ON
088	Flight 2000	Always free play	ON	OFF	ON	OFF	OFF	ON	ON	ON	OUT	IN	ON
132	Flight 2000 V3347	Custom ROM *** WARNING *** READ INFO FIRST. See website for info tx	OFF	ON	ON	ON	ON	OFF	ON	ON	OUT	IN	ON
089	Freefall	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	ON	ON	OFF	OUT	IN	ON
090	Freefall	Always free play	ON	OFF	ON	OFF	OFF	ON	OFF	ON	OUT	IN	ON
091	Galaxy	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	ON	OFF	OFF	OUT	IN	ON
092	Galaxy	Always free play	ON	OFF	ON	OFF	OFF	OFF	ON	ON	OUT	IN	ON
093	Iron Maiden	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	OFF	ON	OFF	OUT	IN	ON
094	Iron Maiden	Always free play	ON	OFF	ON	OFF	OFF	OFF	OFF	ON	OUT	IN	ON
095	Lightning	Stock ROM. No free play	ON	OFF	ON	OFF	OFF	OFF	OFF	OFF	OUT	IN	ON
096	Lightning	Always free play	ON	OFF	OFF	ON	ON	ON	ON	ON	OUT	IN	ON
090	Meteor	Stock ROM. No free play. Factory Bonus X underflow to 256X bug fix	ON	OFF	OFF	ON	ON	ON	ON	OFF	OUT	IN	ON
098	Meteor 7 Digit	V24 7 Digit Displays	ON	OFF	OFF	ON	ON	ON	OFF	ON	OUT	IN	ON
090	Meteor Divide by 10	Scoring divided by ten. No free play	ON	OFF	OFF	ON	ON	ON	OFF	OFF	OUT	IN	ON
100	Meteor Free	Always free play	ON	OFF	OFF	ON	ON	OFF	ON	ON	OUT	IN	ON
						_	_	OFF		OFF			ON
135 137	Meteor V66 Meteor V77	Custom ROM. See website for info txt Custom ROM. See website for info txt	OFF OFF	ON	ON	ON	ON OFF	ON	OFF ON	OFF	OUT	IN IN	ON
				_									ON
101 102	Nine Ball Nine Ball	Stock Rom. No free play	ON ON	OFF OFF	OFF OFF	ON	ON	OFF OFF	ON OFF	OFF ON	OUT	IN IN	ON
		Always free play				_	_	_	_	_			
138	Nine Ball V14	*** BETA *** Custom Rom. Spinner Flips counted	OFF	ON	ON	ON	OFF	ON	OFF	ON OFF	OUT	IN	ON ON
	Orbitor One	Stock Rom. No free play	ON	OFF	OFF		ON	OFF		_	OUT	IN	
104	Orbitor One	Always free play	ON	OFF	OFF	ON	OFF	ON	ON	ON	OUT	IN	ON
105	Orbitor One	No minimum game time. Always free play	ON	OFF	OFF	ON	OFF	ON	ON	OFF	OUT	IN	ON
106	Quicksilver	Stock Rom. No free play	ON	OFF	OFF	ON	OFF	ON	OFF	ON	OUT	IN	ON
107	Quicksilver	Always free play	ON	OFF	OFF	ON	OFF	ON	OFF	OFF	OUT	IN	ON
136	Quicksilver V7	Custom ROM. See website for info txt	OFF	ON	ON	ON	OFF	ON	ON	ON	OUT	IN	ON
108	Seawitch	Stock Rom. No free play	ON	OFF	OFF	ON	OFF	OFF	ON	ON	OUT	IN	ON
109	Seawitch	Always free play	ON	OFF	OFF	ON	OFF	OFF	ON	OFF	OUT	IN	ON
110	Split Second	Stock Rom. No free play	ON	OFF	OFF	ON	OFF	OFF	OFF	ON	OUT	IN	ON
111	Split Second	Always free play	ON	OFF	OFF	ON	OFF	OFF	OFF	OFF	OUT	IN	ON
112	Star Gazer	Stock Rom. No free play	ON	OFF	OFF	OFF	ON	ON	ON	ON	OUT	IN	ON
113	Star Gazer	Always free play	ON	OFF	OFF	OFF	ON	ON	ON	OFF	OUT	IN	ON
114	Star Gazer Home R9	Home ROM by Oliver O.	ON	OFF	OFF	OFF	ON	ON	OFF	ON	OUT	IN	ON
129	Star Gazer Seymour Home V6	Cntr drops for bot roll overs. L/R banks for spinner 10x. Bonus X halved	OFF	ON	ON	ON	ON	ON	ON	OFF	OUT	IN	ON
115	Viper	Stock Rom. No free play	ON	OFF	OFF	OFF	ON	ON	OFF	OFF	OUT	IN	ON
116	Viper	Always free play	ON	OFF	OFF	OFF	ON	OFF	ON	ON	OUT	IN	ON
	Bally Video and Special	REPLACING AS-2518-133 and Conversion Kits	DIP-1	DIP-2	DIP-3	DIP-4	DIP-5	DIP-6	DIP-7	DIP-8	B1	S1	DIP-1 TO DIP-4
117	Baby Pacman	No free play.	ON	OFF	OFF	OFF	ON	OFF	ON	OFF	IN	OUT	OFF
118	Granny and the Gators	No free play.	ON	OFF	OFF	OFF	ON	OFF	OFF	ON	IN	OUT	OFF
119	Grand Slam 2 Player	DIP 25 & 26 ON for free play	ON	OFF	OFF	OFF	ON	OFF	OFF	OFF	IN	OUT	OFF
120	Grand Slam 4 Player	DIP 25 & 26 ON for free play	ON	OFF	OFF	OFF	OFF	ON	ON	ON	IN	OUT	OFF
121	Goldball	No free play.	ON	OFF	OFF	OFF	OFF	ON	ON	OFF	IN	OUT	OFF
122	Goldball Home	Home ROM by Oliver O.	ON	OFF	OFF	OFF	OFF	ON	OFF	ON	IN	OUT	OFF
123	Mystic Star	No free play	ON	OFF	OFF	OFF	OFF	ON	OFF	OFF	IN	OUT	OFF
124	World Defender	No free play	ON	OFF	OFF	OFF	OFF	OFF	ON	ON	IN	OUT	OFF
125	Super Bowl	No free play	ON	OFF	OFF	OFF	OFF	OFF	ON	OFF	IN	OUT	OFF
126	Super Bowl	Custom Free play ROM by Quench	ON	OFF	OFF	OFF	OFF	OFF	OFF	ON	IN	OUT	OFF
127	Saturn 2	No free play	ON	OFF	OFF	OFF	OFF	OFF	OFF	OFF	IN	OUT	OFF
128	Midnight Mauraders		OFF	ON	ON	ON	ON	ON	ON	ON	IN	OUT	OFF
130	Rapid Fire		OFF	ON	ON	ON	ON	ON	OFF	ON	IN	OUT	OFF
131	Black Beauty	Stern Shuffle Board	OFF	ON	ON	ON	ON	ON	OFF	OFF	IN	OUT	OFF
133	Monroe Bowl	Monroe Ball Bowler	OFF	ON	ON	ON	ON	OFF	ON	OFF	IN	OUT	OFF
254	MEMORY CLEAR **	When the LED begins to blink the memory will be cleared.	OFF	OFF	OFF	OFF	OFF	OFF	OFF	ON	EITHER B	1 OR S1 IN	ON

NOTES:

RAM width may be zero ohm jumper shunts (OUT / IN) or a DIP switch (OFF / ON). IN / ON for MPU200 only.

 $B1 and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-200) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-200) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-200) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-200) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-200) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-200) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-100) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-100) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Stern MPU-100) and S1 jumpers set the CPU clock speed. \ B IN for 0.5MHz (Bally -17, -35, -133 and Stern MPU-100). \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set the CPU clock speed. \ S IN for 0.895MHz (Bally -17, -35, -33) and S1 jumpers set$

Jumper shunt U2 Enable is removed when the U1 expanded ROM socket is used.

Clear audits with the Test and NMI Audit Clear buttons after switching games.

Starting in Revision 14 the game select dip switch is oreintated so UP is on and DOWN is off.

** If you experience wrong sounds in a Stern Meteor use the MEMORY CLEAR software (DEC # 254). Power up and when the LED begins to blink the memory has been cleared.

MPU Setup pictures at http://nvram.weebly.com/mpu.html

^{***} DIP 21 Must be off when using original six digit displays in a game that supports seven digit displays.